

GENERATOR AUXILIARY RUN TIME CHART

Generator auxiliary run time chart

kVA	25	45	70	125	150	220	300	400	600	625	750	1000	1250
kW	20	36	56	100	120	176	240	320	480	500	600	800	1000
Fuel consumption at 100% load (GPH)	1.62	2.93	4.4	7.11	8.9	12.5	16.7	22.5	31.7	30.4	31.1	33.6	63.9

Run time hours @100% load

Belly tank	25	27	23	23	33	29	23	18	20	28	18	30	27
------------	----	----	----	----	----	----	----	----	----	----	----	----	----

Auxiliary Tanks Extended run time hours at 100% load

10TCG	155	86											
20TCG	341	188	125	78									
30TCG	486	269	179	111	88								
40TCG	617	341	227	141	112	80							
50TCG	743	411	274	169	135	96	72	54	38	40	39	36	
100TCG	1474	815	543	336	268	191	143	106	75	79	77	71	37